



## WS-01

### Feature:

- Control Lights, Motors, Fans, electrically operated Doors/Locks/Windows/Blinds/Cars or Other Appliances with AC220V, AC85V-260V OR DC12V..
- You can turn on/off the receiver with transmitter (remote control) from any place within a reliable distance; the wireless RF signal can pass through walls, floors and doors.
- This switch can learn different coding remote controls (such as 2262,1527 ect.)
- One/several transmitters can control one/several receivers simultaneously.
- The wireless receiving controller, with high confidentiality, stable performance, low power consumption characteristic, jump line or dial the code switch coding.

### About Receiver:

- Model No.: AK-RK01S-12
  - Channel: 1 CH
- Radio Frequency:315MHZ/433MHZ
- Operating Voltage: DC12V

Operating Type:Jog /Momentary/Non-Latched(Press and hold->On,Release->Off)

Interlock /Latched(Press -> On; Press other button -> Off)

Self-lock/Toggle(Press->On,Press again->Off)

- Coding Type: learning code
- Maximum Working Current: 10A

### About Learning and clearing Method:

Learning:· Press the learning key,green light will be on ,then press remote button ,light flash , which means successfully studied.

Clearing: Hold press learning button about 8 seconds,,indicator from on to off,then press remote ,receiver did not work ,it means clearing code successful.